

PILLBOX PENDANT (LED)**SP-PBX-FR-10 (10")****CAUTION**

TURN OFF THE MAIN POWER AT THE CIRCUIT BREAKER BEFORE INSTALLING THE FIXTURE IN ORDER TO PREVENT POSSIBLE SHOCK

IF YOU ARE UNFAMILIAR WITH PROPER ELECTRICAL WIRING CONNECTIONS OBTAIN THE SERVICES OF A QUALIFIED ELECTRICIAN

GENERAL

- Read all instructions carefully for safe operation and installation.
- All electrical connections must be in accordance with local and national electrical code (N.E.C) standards.
- Remove the fixture and the mounting package from the box and make sure that no parts are missing by referencing the illustrations on the installation instruction. Please contact Blackjack Lighting if any parts are missing or damaged.
- This product is suitable for damp locations.

INSTALLATION**PREPARATION**

1. Remove the fixture from its box.
2. Separate the wire barrier plate(17) from the canopy cover(11) by removing the two screws(16).

MOUNTING

3. Pull the supply wires(2&4) and the house ground wire(6) out of the outlet box(1) and thread them through the large center hole in the ceiling plate(10)
4. Place the ceiling plate(10) over the outlet box(1). Insert mounting screws(9) through the slots in the ceiling plate(10), then tightly secure them into the outlet box(1).

ELECTRICAL CONNECTIONS

5. Connect all of the wires to the driver(18) correctly (DO NOT CONNECT DIRECTLY TO 120V). Red positive to red positive(12&13) and black neutral to black neutral(14&15) using the quick connector(19) provided.
6. Using the wire connectors(8), connect the white supply wire(2) to the white fixture wire(3); connect the black supply wire(4) to the black fixture wire(5); and connect the house ground wire(6) to the fixture ground wire(7).
7. (optional) For the LED driver connect the grey and purple wires to the 0-10v dimming control.

FINAL ASSEMBLY

8. Loosen the strain relief screw(22) and adjust the wire(23) to the required length. Once the wire(23) is at the desired length, retighten the strain relief screw(22). Wrap the excess wire around the u-bracket(20) inside the canopy cover(11).
9. Before mounting the wire barrier plate(17) to the canopy cover(11), secure the wire(23) by tightening the strain relief screw(22).
10. Align the screw holes in the wire barrier plate(17), u-bracket(20) and the canopy housing(11). Then secure them together using the screws provided(16).
11. To secure the canopy cover(11) to the ceiling plate(10) align the three holes on the side of the canopy cover(11) with the holes on the side of the ceiling plate(10). Then secure them together with the three screws(21) provided.
12. Carefully hold the glass diffuser(25) over the fixture(24) outward screw. Then secure them together with the decorative screw(26).


DIMMING

- Fixture Dimming Type: Integrated LED light kit – Universal Dimming(TRIAC, ELV, 0-10V)
- For recommended dimmers see <https://www.blackjacklighting.com/dimming-information>

HARDWARE



Wire Connector(#8) [3 Included] **Mounting Screw(#9)** [2 Included] **Screws(#16)** [2 Included] **Quick Connector(#19)** [1 Included] **Screws(#21)** [3 Included] **Decorative Screw(#26)** [1 Included]



1. OUTLET BOX (By Others)
2. WHITE SUPPLY WIRE
3. WHITE FIXTURE WIRE
4. BLACK FIXTURE WIRE
5. BLACK SUPPLY WIRE
6. HOUSE GROUND WIRE
7. FIXTURE GROUND WIRE
8. WIRE CONNECTORS
9. MOUNTING SCREWS
10. CEILING PLATE
11. CANOPY COVER
12. RED+ FIXTURE WIRE
13. RED+ DC OUT WIRE
14. BLACK- FIXTURE WIRE
15. BLACK- DC OUT WIRE
16. SCREWS
17. WIRE BARRIER PLATE
18. DRIVER
19. QUICK CONNECTOR
20. U-BRACKET
21. SCREWS
22. STRAIN RELIEF SCREW
23. WIRE
24. FIXTURE
25. GLASS DIFFUSER
26. DECORATIVE SCREW